



# Prins Maasdijk

Prins Maasdijk  
 Tuinderweg 37  
 2676 BD Maasdijk  
 Postbus 39  
 2676 ZG Maasdijk  
 Tel: 0174 516240  
 Fax: 0174 518142

## Vermogenstabel Kubota dieselmotoren

| TPM        | 1500 |        | 1800 |        | 2200 |        | 2400 |        | 2600 |        | 2800 |        | 3000 |        | 3600 |        |
|------------|------|--------|------|--------|------|--------|------|--------|------|--------|------|--------|------|--------|------|--------|
| Type Motor | kW   | (PK)   | kW   | (PK)   | kW   | (PK)   | kW   | (PK)   | kW   | (PK)   | kW   | (PK)   | kW   | (PK)   | kW   | (PK)   |
| Z482       | -    | -      | -    | -      | 5.8  | (7.8)  | 6.3  | (8.4)  | 6.9  | (9.2)  | 7.4  | (9.9)  | 7.9  | (10.6) | 9.3  | (12.5) |
| Z602       | -    | -      | -    | -      | 7.1  | (9.5)  | 7.8  | (10.5) | 8.4  | (11.3) | 9.0  | (12.1) | 9.6  | (12.9) | 11.6 | (15.5) |
| D722       | -    | -      | -    | -      | 8.7  | (11.7) | 9.5  | (12.7) | 10.3 | (13.8) | 11.0 | (14.7) | 11.9 | (16.0) | 14.0 | (18.8) |
| D902       | -    | -      | -    | -      | 10.8 | (14.5) | 11.7 | (15.7) | 12.6 | (16.9) | 13.6 | (18.2) | 14.5 | (19.4) | 17.5 | (23.5) |
| D905       | 7.4  | (9.9)  | 8.9  | (11.9) | 11.0 | (14.7) | 11.9 | (16.0) | 13   | (17.4) | 14.0 | (18.8) | 14.9 | (20.0) | 17.5 | (23.5) |
| D1005      | 8.2  | (11.0) | 9.8  | (13.1) | 12.3 | (16.5) | 13.4 | (18.0) | 14.5 | (19.4) | 15.7 | (21.0) | 16.8 | (22.5) | 19.4 | (26.0) |
| D1105      | 9.5  | (12.7) | 11.5 | (15.4) | 13.7 | (18.4) | 15.0 | (20.1) | 16.2 | (21.7) | 17.5 | (23.5) | 18.7 | (25.1) | -    | -      |
| D1105T     | -    | -      | -    | -      | 17.2 | (23.1) | 18.8 | (25.2) | 20.4 | (27.3) | 21.9 | (29.4) | 23.5 | (31.5) | -    | -      |
| V1305      | 10.9 | (14.6) | 13.1 | (17.6) | 16.4 | (22.0) | 17.9 | (24.0) | 19.4 | (26.0) | 20.9 | (28.0) | 22.4 | (30.0) | 25.7 | (34.5) |
| V1505      | 12.5 | (16.8) | 15.1 | (20.2) | 18.4 | (24.7) | 20.0 | (26.8) | 21.6 | (29.0) | 23.4 | (31.4) | 25.0 | (33.5) | -    | -      |
| V1505T     | -    | -      | -    | -      | 23.0 | (30.8) | 25.1 | (33.6) | 27.2 | (36.5) | 29.2 | (39.1) | 31.3 | (42.0) | -    | -      |
| D1403      | 12.1 | (16.2) | 14.2 | (19.0) | 18.1 | (24.3) | 19.3 | (25.9) | 20.6 | (27.6) | 21.6 | (29.0) | -    | -      | -    | -      |
| D1503M     | -    | -      | -    | -      | 18.4 | (24.7) | 19.9 | (26.7) | 21.4 | (28.7) | 22.8 | (30.6) | -    | -      | -    | -      |
| D1703M     | 15.0 | (20.1) | 18.1 | (24.3) | 20.5 | (27.5) | 22.3 | (29.9) | 23.9 | (32.0) | 25.6 | (34.3) | -    | -      | -    | -      |
| D1803M     | -    | -      | -    | -      | 23.1 | (31.0) | 25.1 | (33.6) | 27.1 | (36.3) | -    | -      | -    | -      | -    | -      |
| V1903      | 16.4 | (22.0) | 19.4 | (26.0) | 23.9 | (32.0) | 25.7 | (34.5) | 27.5 | (36.9) | 29.1 | (39.0) | -    | -      | -    | -      |
| V2003M     | -    | -      | -    | -      | 24.6 | (33.0) | 26.6 | (35.7) | 28.5 | (38.2) | 30.4 | (40.8) | -    | -      | -    | -      |
| V2203M     | 20.1 | (26.9) | 24.2 | (32.4) | 27.0 | (36.2) | 29.3 | (39.3) | 31.4 | (42.1) | 33.5 | (44.9) | -    | -      | -    | -      |
| V2403M     | -    | -      | -    | -      | 30.5 | (40.9) | 33.1 | (44.4) | 35.6 | (47.7) | -    | -      | -    | -      | -    | -      |
| V2003M-T   | 22.5 | (30.2) | 27.1 | (36.3) | 32.9 | (44.1) | 35.7 | (47.9) | 38.4 | (51.5) | 41.0 | (55.0) | -    | -      | -    | -      |
| V3300      | 28.9 | (38.7) | 35.3 | (47.3) | 43.4 | (58.2) | 47.0 | (63.0) | 50.5 | (67.7) | -    | -      | -    | -      | -    | -      |
| V3800DI    | -    | -      | -    | -      | 49.8 | (66.8) | 54.1 | (72.5) | 58.4 | (78.3) | -    | -      | -    | -      | -    | -      |
| V3300-T    | 35.3 | (47.3) | 43.1 | (57.8) | 52.7 | (70.6) | 57.2 | (76.7) | 61.6 | (82.6) | -    | -      | -    | -      | -    | -      |
| V3800DI-T  | -    | -      | -    | -      | 59.8 | (80.2) | 65.0 | (87.1) | 70.2 | (94.1) | -    | -      | -    | -      | -    | -      |

Netto intermitterend vermogen  
 Norm: SAE-J1350

